

## **FAST-SWIR Family**



SHORT WAVE INFRARED CAMERAS

## **KEY FEATURES**



**HIGH FRAME RATE** 



**SPECTRAL BAND OPTIONS** 



**HIGH SENSITIVITY** 





**OPTIC MOUNTS** 

The FAST-SWIR camera line is the fastest infrared camera line available in the SWIR band. Ideal for analyzing dynamic events, the FAST-SWIR infrared cameras are also highly sensitive, thanks to their unique low noise detector.



## **FAST-SWIR Family**





Welding Target Ranging

## **FAST-SWIR Series**

SPECIFICATIONS	FAST S800	FAST S2K
Pixel Size	20 μm x 20 μm	20 μm x 20 μm
Spectral Band	0.9 μm to 1.7 μm opt.: 0.4 μm to 1.7 μm (VisNIR)	0.9 μm to 1.7 μm opt.: 0.4 μm to 1.7 μm (VisNIR)
Spatial Resolution	640 × 512 pixels	640 × 512 pixels
Window of Interest	Yes   Minimum size 32 x 4 pixels	Yes   Minimum size 32 x 4 pixels
Max. Frame Rate (Full Window)	865 Hz 33 000 Hz @ 32 x 32	1 730 Hz
Max. Frame Rate (Subwindow)	865 Hz 33 000 Hz @ 32 x 32	150 000 Hz @ 32 x 4
Roic Noise	High gain: 60 e-; low gain: 138 e	High gain: 60 e-; low gain: 138 e
Dark Current	0.19 x 106 e-/s/pixel or 30 fA @ 200mV bias at 288 K	0.19 x 106 e-/s/pixel or 30 fA @ 200mV bias at 288 K
Exposure Time Range	1 µs up 40 ms @ 25 °C sensor temperature (high gain mode) or up to 100 ms @ 268 K sensor temperature (high gain mode)	1 µs up 40 ms @ 25 °C sensor temperature (high gain mode) or up to 100 ms @ 268 K sensor temperature (high gain mode)

	OTHER SPECS & FEATURES	
Camera Control	Camera Control Camera Link (Serial LVDS Line on Camera Link Port 1)	
Camera Cooling	Forced Air Cooling	
Ambient Operating Temperature	0 °C to 50 °C	
Dimentions	140 W x 135 H x 90 L mm	
Weight (Camera Head)	2 kg	







telops.com

